MONITORIZACION DEYE-SOFAR-TURBO

SE HACEN LOS PASOS DESDE EL MÓVIL NO HAY QUE TOCAR NI LA APP NI EL INVERSOR

1.- ANTES DE HACER LA CONFIGURACION HAY QUE DESCONECTAR LOS DATOS MÓVILES SOLO DEJAR EL WIFI ACTIVO, Luego con el móvil buscamos las redes WIFI disponibles y seleccionamos la que dice AP_XXXXXX (Nº SERIE DE SU INVERSOR)



1.1 HAY QUE COMPROBAR EN LA ANTENA NEGRA DEL INVERSOR LAS LUCES:

La luz NET tiene que estar apagada , la luz COM tiene que estar fija encendida , y por último la luz READY tiene que estar encendida pero parpadeando.

EJEMPLO:



SI LAS LUCES ESTAN CORRECTAS PODEMOS CONTINUAR, de lo contrario tendríamos que reiniciar la antena con el botón negro que está en su lateral, esperamos que se regenere y luego comprobamos, si las luces siguen de manera errónea no cogerá la configuración tiene que ir un técnico al domicilio no continúe los pasos.

2.- Nos pedirá una contraseña la cual está en la pegatina que tiene la antena debajodel inversor que dice "PWD".



3.- Verificar que está conectado a la red y le dirá "Sin internet" ESTO ES CORRECTO y Si sale un cuadro preguntando si quiere usar datos móviles decir que "No".



4.- Una vez conectado a la red WIFI del inversor tenemos que irnos a un NAVEGADOR (**Google Chrome,** se recomienda usarlo si tiene androide **Si usted tiene un dispositivo **Apple** es recomendable utilizar el navegador **Safari o EDGE**) y colocar la siguiente dirección IP: 10.10.100.254 y darle a Buscar. (ESCRIBIR BIEN LOS PUNTOS Y NUMEROS)



5.- Nos pedirá usuario y contraseña (TODO EN MINUSCULAS Y ES IGUAL EL USUARIO QUE LA CONTRASEÑA) y colocaremos en usuario: admin y encontraseña: admin y le daremos Iniciar
Sesión. TENEMOS QUE SER UN POCO RAPIDOS SI NO, NO PILLARÁ LA CONFIGURACIÓN

15:54 🕓 📭 🚓 ···				ር) ው ው . በ 奈 🐵					
$\hat{\Box}$	()	10.1(0.100.	254			⊢	5	
I	nicia	ir se	esiór	١					
http://10.10.100.254 necesita un nombre de usuario y una contraseña. Tu conexión con este sitio web no es privada Nombre de usuario									
	admir	า							
	Contrase	eña							
									.
				(Cance	lar	Inicia	r sesio	ón
1	2	3	4	5	6	7	8	9	0
q	W	е	r	t	у	u	i	0	р
а	S	d	f	g	h	j	k	Ι	ñ
\uparrow	Z	: >	< C	: \	/ k	o r	n r	n	×
?12	з,								~
				•	•		4		

15:57 🛇 📭 📭 \cdots		ርን ው ው .			
	▲ 10.10.100.254/index_	+	3:		
			Φ文 (Eng		
Status Wizard Quick Set Advanced Upgrade Restart Reset	Inverter information Inverter serial number Firmware version (main) Firmware version (slave) Inverter model Rated power Current power Yield today Total yield Alerts Last updated Device information		The device can be used as a wireless access point (AP mode) to facilitate users to configure the device, or, or can also be used as a wireless information terminal (STA mode) to connect the remote server via wireless router. Status of remote server • Not connected: Connection to server failed last time. If under such status, please check the issues as follows: (1) check the device information to see whether mortain to see whether and the such status of the second set of the second set of the second set of the second set of the second set whether second set of the second set of the second set of the second set of the second set of the second set of the second set of the second set of the second set of the second second set of the seco		
	+ Remote server information		IP address is obtained or not; (2) check if the router is connected to internet or not (3) check if a firewall is set on the cruter or not		

6.- Aparecerá una página principal como esta:

 7.- Click en la parte izquierda en la segunda opción donde dice
 "WIZARD", seleccionar la RED WIFI del DOMICILIO y luego ABAJO darle a "NEXT".

15:	57 (S) e, e,		() 0 0) ଲ ଲ (ଲ (83
	10.10.100.2	54/index_	+	3	•
Status Wizard Quick Set Advanced Upgrade Restart Reset	Please select your curr Site Survey NVR083a2f0bff31 3:3A2FE NVR083a2f10bff31 3:3A2FE NVR083a2f10bff31 3:3A2FE NVR083a2f14c7557 8:3A2F4 R8D Iberia lot R8D Iberia lot R8D Iberia for VPN ★Note: When RSSI of the f than 15%, the connection f the device and router. Add wireless network of Encryption rate (SID) (Note: case sensitive) Encryption adjorithm (A	ent wireless networ IFF-31 100 13 B4 11 C75 57 82 13 UB1C3:45 54 6 31:C3:45 54 6 selected WiFi network map be unstable, please shorten the distance be Refree nanually: PA2PSK v Sa 4	k: is lower ie select setween ah	He The setup wiz, you to comple setting within a	₽\$ English slp ard will assist to the device one minute.

8.- Pedirá colocar la contraseña o password del WIFI DEL DOMICILIO y luego darleabajo a "NEXT".

16:05 🛱 🛱 🖗 ···			ו. פ∂ פ	82	
1 0.10.100.25	4/index_	+	3	:	
			He	中文 i English elp	
Please fill in the following informa	ation:				
			function of DH	Support the ICP to obtain	
Password (8-64 bytes)			IP address aut Please select of	omatically. disable and	
(Note: case sensitive)	Show Password		add it manuall does not supp	y if your router ort such	
			function.		
Obtain an IP address automatically	Enable ~				
IP address					
Subnet mask					
Gateway address		_			
DNS server address					
1 2	Back Net	xt			
	Please fill in the following information (Note: case sensitive) Obtain an IP address automatically IP address Subnet mask Gateway address DNS server address	10.10.100.254/index_ Dease fill in the following information: Password (8-64 bytes) (Note: case sensitive) Ditain an IP address automatically IP address automatically IP address Gateway address DNS server address DNS server address 1 2 3 4	A 10.100.254/index.	10.10.100.254/index_ + 3 Please fill in the following information: Password (8-64 bytes) (Net: case sensitive) Show Password Obtain an IP address automatically IP address Subnet mask Gateway address DNS server address I 1 2 3	

9. En la página 3 darle a **"NEXT"** sin tocar mas nada y luego en la **4ta** pantalla darle a **"OK"** sin tocar mas nada y tiene que ser como la imagen y decir setting complete para que se configure correctamente.

16	:05 ஷ ஷ 🦘 \cdots	(כ) ייסי	୦ .
	10.10.100.254/index_	+	3
			₽文 Engl
Status Wizard Quick Set Advanced Upgrade Restart Reset	Enhance Security You can enhance your system security by choosing the foll methods Hide AP Change the encryption mode for AP Change the user name and password for Web server	owing	Change the encryption mode for AP If you set password for the AP network, you will need to enter the password to connect to AP. Change the user name and password for Web server If you change the username and password for the web server, you will need to enter the new username and password to get access to the setting page.
	Back N	lext	



10- Verificar que salga **Setting Complete Y** darle OK y salirse sin apretar nada mas.

Si le sale carita triste es porque se ha demorado mucho tiene que hacer los mismo pasos nuevamente desde cero (PUEDE INTENTARLO DESDE EL ORDENADOR QUE TIENE MENOS ERRONES) y si lo hace todo y le dice completado pero no se conecta, no hay mas que hacer si no que tiene que ir un técnico al domicilio a ver que pasa. Hay que aceptar protocolo que se lo enviarán a su correo.

